


# 2010S-WE

## SOCKET SWITCHED AUTO SWITCHED SINGLE 10A WITH SAFETY SHUTTER



### Main

|                  |                  |
|------------------|------------------|
| Range of product | Series 2000      |
| Colour           | White electric   |
| Product brand    | Clipsal          |
| Quantity per set | Set of 1         |
| Cover type       | Full cover plate |

### Complementary

|                                |                         |
|--------------------------------|-------------------------|
| Colour code                    | WE                      |
| Marking                        | Without marking         |
| Protection type                | Fingersafe              |
| Local signalling               | Without light indicator |
| Fixing mode                    | By screws               |
| [In] rated current             | 10 A                    |
| [Ue] rated operational voltage | 250 V AC                |
| Depth                          | 31 mm                   |
| Length                         | 116 mm                  |
| Width                          | 76 mm                   |
| Fixing center                  | 84 mm                   |

### Environment

|           |  |
|-----------|--|
| standards | AS/NZS 3100<br>AS/NZS 3112<br>AS/NZS 3133 :approval number S/1 |
|-----------|--|

### Offer Sustainability

|                                  |   |
|----------------------------------|---|
| Sustainable offer status         | Not Green Premium product   |
| RoHS (date code: YYWW)           | Compliant - since 0854 - Schneider Electric declaration of conformity |
| REACH                            | Reference contains SVHC above the threshold                           |
| Product end of life instructions | Need no specific recycling operations                                 |

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.