

3025RCD30-VW

Clipsal Iconic - 2 switched sockets - RCD 30 mA - vivid white



Main

| | |
|-------------------------------|-----------------------|
| Range | Clipsal Iconic |
| Product or component type | Switched socket |
| Device presentation | Complete product |
| Outlet poles configuration | 2P + E with shutter |
| Type of packing | Polybag |
| Quantity per set | Set of 4 |
| Sale per indivisible quantity | 1 |
| Rated current | 10 A, 250 V AC, 50 Hz |

Complementary

| | |
|---------------------------------------|---|
| Device mounting | Flush |
| Number of power socket outlets | 2 |
| Number of rocker | 2 |
| Outlet standard | Australian |
| Outlet standard description | With earthing contact |
| Outlet standard | Australian/New Zealand |
| Ground lug position | Straight 180° position |
| Fixing mode | By screw |
| Installation direction | Horizontal |
| Colour tint | Vivid white (VW) |
| Surface finish | Matt |
| Ambient air temperature for storage | 0...60 °C |
| Ambient air temperature for operation | 0...45 °C |
| Relative humidity | 10...95 % |
| Electrical durability | 12000 cycles |
| Screwdriver shape | Philips No 2 Square drive no 1 (SQ1) |
| Clamping connection capacity | 1 x 2.5...4 x 2.5 mm ² (rigid) 1 x 2.5...4 x 2.5 mm ² (rigid) 1 x 2.5...4 x 2.5 mm ² (stranded) 1 x 2.5...4 x 2.5 mm ² (flexible) |
| Wire stripping length | 16 mm |
| Material | ABS (acrylonitrile butadiene-styrene) for cover frame POM (polyoxymethylene) for shutter POM (polyoxymethylene) for shutter PC (polycarbonate) for fixing frame PP (polypropylene) for rocker PC (polycarbonate) for cover frame |
| Height | 120 mm |
| Width | 78 mm |
| Depth | 44 mm |
| Standards | AS/NZS 3112 AS/NZS 3190 |

Environment

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.