



Main

Complementary

| | |
|----------------------------|---|
| Range of product | ARGUS standard movement detector |
| Range | ARGUS |
| Product or component type | Presence detector with IR receiver |
| Load type | LED lighting: : 100 W Compact fluorescent lamp: : 100 W Motor: : 100 W Relay: : 5 A - 250 V Incandescent lamps: : 1000 W - 230 V Halogen lamp: : 900 W - 230 V Halogen lamp with standard electronic transformer: 250 VA Halogen lamp with standard ferromagnetic transformer: 500 VA Capacitive: : 6 A 21 µF Capacitive: : 10 A 14 µF Fluorescent tube: 200 VA |
| Colour tint | White |
| Network frequency | 50/60 Hz |
| Input function | Switch |
| Output voltage | 220...250 V |
| Output current | 10 A |
| Number of channels | 2 |
| Control type | Movement sensor |
| Function available | Switching, toggling, dimming |
| Light intensity adjustment | 5...1000 lux |
| Horizontal detection angle | 360 ° |
| Cable length | 0.035 m |
| Detection face | Radius: 3500 mm |
| Mounting height | 2.5 m |

Environment

| | |
|-------------------------|------|
| IP degree of protection | IP20 |
|-------------------------|------|

Offer Sustainability

| | |
|----------------------------------|---|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 1611 - Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Available |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.