



Main

| | |
|------------------|----------|
| Product brand | Clipsal |
| Range of product | Series 4 |

Complementary

| | |
|--------------------------------|--|
| Curve code | C |
| Number of poles | 3 |
| [In] rated current | 2 A |
| Number of modules | 3 |
| [Ue] rated operational voltage | 415 V |
| Breaking capacity | 6 kA conforming to EN 60898 |
| Network type | AC |
| Network frequency | 50/60 Hz |
| [Ui] rated insulation voltage | 440 V |
| IP degree of protection | IP20 IEC 60529 IP40 modular enclosure IEC 60529 |

Environment

| | |
|---------------------------------------|---|
| ambient air temperature for operation | -25...70 °C |
| ambient air temperature for storage | -40...70 °C |
| standards | AS/NZS 60898 |
| tropicalisation | 2 IEC 60068-1 |
| relative humidity | 95 % 55 °C |
| height | 81 mm |
| width | 54 mm |
| depth | 78.5 mm |
| product weight | 310 g |
| mechanical durability | 20000 cycles |
| electrical durability | 20000 cycles |
| connections - terminals | Screw terminal 0.75...16 mm ² rigid 1 Screw terminal 0.33...10 mm ² flexible 1 Screw terminal 0.33...10 mm ² flexible with ferrule 1 |
| wire stripping length | 13 mm |
| tightening torque | 2 N.m |

Offer Sustainability

| | |
|----------------------------------|---|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 0627 - Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Need no specific recycling operations |

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.