

56SO313LE-GY

56 Series Socket - 3 Pin - 13A - 250V - Less
Enclosure - Grey



Main

| | |
|---------------------------|------------------------|
| Range of product | Series 56 |
| Range | Clipsal - 56 Series |
| Product brand | Clipsal |
| Product or component type | Socket-outlet |
| Device application | Power supply |
| Colour | Grey RAL 7035 |
| Outlet standard | Australian/New Zealand |

Complementary

| | |
|--------------------------------|---|
| Plug, socket category | Low voltage |
| Device mounting | Surface |
| Mounting mode | External mounting |
| [In] rated current | 13 A |
| [Ue] rated operational voltage | 250 V AC @ 50 Hz EN 60309-2 |
| Poles description | 1P + N + E |
| Voltage colour | Blue |
| Duration | 6 h |
| Material | Polycarbonate for the cover |
| Contacts material | Brass for the screws |
| Connections - terminals | Screw terminals 1.5...6 mm ² cable stiffness rigid or stranded |
| Tightening torque | 0.8 N.m |
| Socket number | 1 |
| Outlet standard | Industrial |
| Product weight | 0.22 kg |
| Depth | 55 mm |
| Width | 101 mm |
| Height | 107 mm |
| Targeted country | Australia |

Environment

| | |
|---------------------------------------|-------------|
| ambient air temperature for operation | -25...75 °C |
| standards | BS 1363-1 |

Offer Sustainability

| | |
|----------------------------------|---|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 1650 - Schneider Electric declaration of conformity |
| REACH | Reference contains SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Need no specific recycling operations |

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.