



### Main

Device short name	F
Enclosure type	Enclosure standard environment indoor
Factory modification	Low pressure cut-off (AUTO-START-OFF) operates roughly 10 PSIG below cut-in 0.06 inch pulsation plug
Product specific application	Control electrically driven water pumps
Range of product	Square D Pumptrol
Switch application	Standard

### Complementary

Adjustable range on rising pressure	25...80 psi
Approximate adjustable differential	20...30 psi
Cable entry	Conduit entry 1217X60 rubber plug
Depth	2.78 in
Electrical connection	Slip-on terminal
Fixing mode	By brackets
Fluid connection type	0.25 inch NPSF internal
Height	2.8 in
Material	Zinc plated steel flange
Materials in contact with fluid	Nitrile (Buna-N) diaphragm
Maximum pressure	220 psig
Motor power hp	2 hp 115 V AC 1 phase 3 hp 230 V AC 1 phase 5 hp 230 V AC 3 phases 1 hp 460/575 V AC 3 phases 3 hp 115 V AC 3 phases
Number of poles	2
Permissible voltage	<= 575 V AC
Pressure actuator	Diaphragm
Pressure setting range	30...50 psi
Product weight	1.13 lb(US)
Range on decreasing pressure	5...60 psi
Scale type	Adjustable differential
Switch function	DPST
Width	3.76 in

### Environment

NEMA degree of protection	NEMA 1
product certifications	UL listed file E12158 CCN NKPZ CSA file LR25490

### Offer Sustainability

Sustainable offer status	Not Green Premium product
RoHS (date code: YYWW)	Will not be Compliant
REACH	Reference not containing SVHC above the threshold
Product environmental profile	Available
Product end of life instructions	Available

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.